

Decentralized Admission Control for Power-Controlled Wireless Links

Sławomir Stańczak, Michał Kaliszan and Nicholas Bambos

Abstract

This paper deals with the problem of admission control/channel access in power-controlled decentralized wireless networks, in which the quality-of-service (QoS) is expressed in terms of the signal-to-interference ratio (SIR). We analyze a previously proposed admission control algorithm, which was designed to maintain the SIR of operational (active) links above some given threshold at all times (protection of active links). This protection property ensures that as new users attempt to join the network, the already established links sustain their quality. The considered scheme may be thus applicable in some cognitive radio networks, where the fundamental premise is that secondary users may be granted channel access only if it does not cause disturbance to primary users.

The admission control algorithm was previously analyzed under the assumption of affine interference functions. This paper extends all the previous results to arbitrary standard interference functions, which capture many important receiver designs, including optimal linear reception in the sense of maximizing the SIR and the worst-case receiver design. Furthermore, we provide novel conditions for protection of active users under the considered control scheme when individual power constraints are imposed on each link. Finally, we consider the possibility of a joint optimization of transmitters and receivers in networks with linear transceivers, which includes linear beamforming in multiple antenna systems. Transmitter optimization is performed alternately with receiver optimization to generate non-decreasing sequences of SIRs. Numerical evaluations show that additional transmitter side optimization has potential for significant performance gains.

Index Terms

S. Stańczak and M. Kaliszan are with Fraunhofer German-Sino Lab for Mobile Communications Einsteinufer 37, D-10587 Berlin, Germany Email: {slawomir.stanczak, michal.kaliszan}@hhi.fraunhofer.de

N. Bambos is with the Department of Electrical Engineering 350 Serra Mall, Stanford University, Stanford, CA 94305 Email: bambos@stanford.edu

This work was presented in part at the 42nd Asilomar Conference on Signals, Systems, and Computers, Monterey, CA, USA.

distributed admission and power control, interference functions, cognitive radio, beamforming

I. INTRODUCTION

Admission control is an important element of wireless communication systems and its significance stems from the nature of most applications, where arrivals of new users as well as departures of existing ones occur on an irregular basis. Reallocating the available resources from the scratch after such arrivals or departures is at best highly inefficient, in many cases simply infeasible. This necessitates the development of admission control schemes to decide whether or not a new user is allowed to join the network, and how should the admission be organized so that the existing (active) users are not disturbed. Recently, admission control has acquired additional importance in the context of cognitive radio, where the necessary condition for allowing secondary (unlicensed) users to access some given resources is that the operation of primary (licensed) users remains unhindered.

An interesting contribution in the field of admission control is the work presented in [1], where the authors addressed the admission control problem¹ in power-controlled decentralized wireless networks. The main idea is the introduction of an active link protection (ALP) mechanism to sustain the SIR of active links above required thresholds, as new links attempt to access the same channel by gradually increasing their transmit powers (in a guarded manner). The active links are endowed with an SIR protection margin to cushion the effect of increased interference.

The work of [1] was preceded by extensive research in the area of power control. In particular, References [2], [3] proposed a distributed asynchronous on-line power control algorithm, which can satisfy user-specific SIR requirements at the minimum transmitter powers. It converges geometrically fast to a global unique optimum, provided that the users have feasible SIR requirements. Yates [3] further showed that the convergence result remains valid if the interference power at each receiver output is any standard (interference) function of the transmit powers. The class of standard interference functions is described by three (non-restrictive) axioms, namely positivity, scalability and monotonicity. Such an interference model captures most practical receiver designs, including the worst-case receiver design and optimal linear reception in the sense of maximizing

¹In this paper, it may be more accurate to think of “channel access” rather than “admission control”. We use the latter term as both concepts are closely related in decentralized networks.

the SIR. It is also general enough to incorporate cross-layer effects, and it serves as a theoretical basis for many algorithms. The analysis in [1] considered linear interference, which may also be viewed as a special case of interference functions introduced in [3].

A. Paper contribution and structure

In this paper, we extend the work of [1] in the following three directions:

- (a) We incorporate the axiomatic interference model of [3] by assuming that the interference perceived by any user/link is characterized by a standard interference functions. This model includes linear interference functions assumed in [1] as a special case.

It was already pointed out by [3, Sect. V.C] that the ALP property of the algorithm in [1], which is the ability to maintain the SIR values of the active links above a given SIR targets at all times, carries over to standard interference functions. In this paper, we show however that the algorithm preserves its *all* properties under standard interference functions. All the results presented in [1] can be thus derived from the simple axiomatic framework. These results are presented in Sect. III.

- (b) We take into consideration individual power constraints on each link and prove sufficient conditions for the algorithm to provide the ALP.

As mentioned in [3, Sect. V.C] and [1, Sect. VII], the ALP is not preserved when the limitations on transmit powers are taken into account. As a remedy, the authors of [1] suggested equipping the admission control scheme with a forced drop-out mechanism which causes new/inactive links to drop out when they push active ones beyond their maximum powers. In this paper, we provide novel conditions for having the ALP property. Of particular interest may be “on-line” conditions that guarantee the ALP, provided that the network is in a some state, which is shown to be achieved in a finite time; as long as such a state is not achieved, no new users are allowed to access the channel. These results can be found in Sect. IV.

- (c) We assume a wireless network equipped with optimal linear receivers in the sense of maximizing each SIR, which includes multiple antenna systems with optimal linear receive beamforming [4]. We investigate the impact of *transmitter* side optimization (in addition to the receiver side optimization) when the links are not fully admissible.

Based on the ideas of [5], transmitter optimization is performed alternately with receiver optimization so as to generate a sequence of non-decreasing SIRs. Numerical evaluations show

that additional transmitter side optimization has a potential for huge performance gains. The problem of linear transceiver optimization is addressed in Sect. V.

B. Further related work

The problem of power control in wireless networks has been an active research area for more than the past two decades. Early works focused on centralized and distributed power control, including the so-called max-min SIR balancing problem (SIR: signal-to-interference ratio) and the QoS-based power control aiming at satisfying given desired SIR levels (SIR targets) with a minimum total transmit power. Both approaches have been extensively studied and are fairly well understood [6], [7], [2], [3], [8], [9], [10], [11], [12], [13], [14]. The work evolved towards distributed power control algorithms (see for instance [2], [3] and [15] for combined power control and cell-site selection). The axiomatic framework in [3] allowed for extracting more general properties of various power control algorithms. A slightly different framework of general interference functions was proposed in [4] and was used as a basis for analysis of properties of selected classes of interference functions [16], [17].

The early works on power control focused on the convergence behavior of the algorithms. The DPC/ALP algorithm proposed in [1] and analyzed in this paper was one the first attempts to provide certain performance guarantees during the transient phase, before the algorithm converged. In [18], the authors use tools from control theory to analyze the behavior of the iterative power control algorithm with linear interference ([2]). This allows them to prove existence of invariant sets in the SIR domain and thus provide conditions under which links are protected from dropping below the required SIR target.

A framework for adapting the transmission power under varying system conditions so that the perceived QoS is guaranteed is considered in [19]. The authors of [13] present a cross-layer design framework for contention-based wireless networks with scheduling and power control phases combined in a alternating way. Reference [20] considered power control in multi-cell networks as a team optimization problem and also analyzed admission control for the presented model. A different approach is followed in [21], where channel reservation is combined with power control to eliminate the need for incremental power-up phase of the inactive users. Reference [22] proposed admission and congestion control scheme for large networks with homogeneous user distribution, which takes both intra- and inter-cell interference into account

as well as power constraints. Admission control for the uplink of a multi-cell wireless network is considered in [23]. Two approaches were proposed based on admission criteria or connection removal. Other interesting and related contributions on the subject include [24], [25] and [26].

The authors of [27] approached the admission control problem for a network with both multiple user classes and multiple service classes by formulating it as a homotopy method. In [28], the authors suggested proportional reduction of SIR requirements as a control mechanism in the case of overload. Several attempts have also been made to use Game Theory for the considered problem. In [29], the authors presented auction-based mechanisms for allocating power, which are capable of achieving a weighted max-min fair SINR allocation or maximizing the total utility. Reference [30] considered a distributed power control scheme in which each user announces a price to be paid by other users for the interference they cause. The authors of [31] analyzed the case of linear interference functions and introduced a system parameter called discriminant. Two distributed protocols are considered, in which the value of the discriminant is used to decide whether a new user can be admitted to the system. References [32] and [33] proposed distributed power control schemes in which some cost for each mobile is used. Finally, in a recent publication [34], the starting point for the analysis is the algorithm proposed by [1], which is also the starting point for our paper. The authors [34] analyzed the tradeoff between energy consumption and robustness.

The basic idea of cognitive radio, proposed in [35], is to identify highly underutilized frequency bands of the radio spectrum and then allow unlicensed users to access these bands. Various approaches to implementing cognitive radio networks have been considered ever since. These approaches include among others spectrum sensing and spectrum sharing using centralized or decentralized cognitive MAC protocols; for an overview we refer to [36].

There is a close connection between the concepts of cognitive radio and admission control, as implementing a cognitive radio network in a distributed environment requires an appropriate access scheme. This approach is followed by the authors of [37]. Primary users have a certain QoS requirements that cannot be violated. The goal is to maximize the number of admitted secondary users, where each secondary user, if admitted, also has a certain QoS requirement. The problem is NP-hard, and the authors proposed a convex approximation algorithm.

II. SYSTEM MODEL, ASSUMPTIONS AND DEFINITIONS

We consider an arbitrary power controlled wireless network with K (logical) links that are referred to as *users*. Let $\mathcal{K} := \{1, \dots, K\}$ and let $\mathbf{p} = (p_1, \dots, p_K) \geq 0$ be the power vector (allocation), whose k th coordinate is transmit power of user k at some time instant. In this paper, we assume that the wireless channel is arbitrary (chosen randomly) but fixed. This is a reasonable assumption for a broad class of networks in which channels vary slowly so that optimization algorithms need significantly less time than the coherence time. The performance measure of interest is the signal-to-interference ratio (SIR), which is defined to be

$$\text{SIR}_k(\mathbf{p}) = p_k / I_k(\mathbf{p}) \geq 0.$$

Here and hereafter, $I_k : \mathbb{R}_+^K \rightarrow \mathbb{R}_{++}$ is any standard interference function that fulfills the following axioms:

Definition 1 (Standard Interference Function [3]): We say that $I_k : \mathbb{R}_+^K \rightarrow \mathbb{R}, k \in \mathcal{K}$, is a standard interference function if each of the following holds.

- A1 $I_k(\mathbf{p}) > 0$ for all $\mathbf{p} \geq 0$ (*positivity*).
- A2 $I_k(\mu\mathbf{p}) < \mu I_k(\mathbf{p})$ for any $\mathbf{p} \geq 0$ and $\mu > 1$ (*scalability*).
- A3 $I_k(\mathbf{p}^{(1)}) \geq I_k(\mathbf{p}^{(2)})$ if $\mathbf{p}^{(1)} \geq \mathbf{p}^{(2)}$ (*monotonicity*).

It may be verified that the linear (affine) interference function assumed in [2], [1] and given by

$$I_k(\mathbf{p}) = (\mathbf{V}\mathbf{p} + \mathbf{z})_k = \sum_{l \in \mathcal{K}} v_{k,l} p_l + z_k \quad (1)$$

satisfies the axioms. Here, $\mathbf{V} = (v_{k,l})$ is the so-called gain matrix, $v_{k,l} \geq 0$ with $v_{k,k} = 0$ are (effective) power gains determined by the transceiver structure, wireless fading channel etc, and $\mathbf{z} = (z_1, \dots, z_K) > 0$ is the noise vector. Note that $v_{k,l} = V_{k,l}/V_k \geq 0$, where $V_k > 0$ is the signal power gain and $V_{k,l}$ denotes the interference power gain, is independent of the power allocation. This is for instance the case when each link employs the matched-filter receiver or linear successive interference cancellation receiver.

One can however go one step further in assuming that the power gains – and with it the interference powers – depends on some *adaptive* receive strategy to be chosen depending on power allocation. Assuming the power vector $\mathbf{p} \geq 0$ and some adjustable receive strategy²

²In general, $\mathbf{U}$ is a compact subset of the unit sphere chosen so as to take into account potential constraints on the receiver structure.

$\mathbf{u}_k \in \mathcal{U} = \{\mathbf{u} : \|\mathbf{u}\|_2 = 1\}$, a more general model of the (effective) interference power at the output of receiver k is

$$\varrho_k(\mathbf{p}, \mathbf{u}_k) = \sum_{l \in \mathcal{K}} v_{k,l}(\mathbf{u}_k) p_l + z_k(\mathbf{u}_k). \quad (2)$$

We see that the receive strategies influence the power gains $v_{k,l}, l \neq k$, and the effective noise power z_k . It is pointed out that the k th receive strategy impacts only the interference of user k . Now the interference function under an optimal receiver in the sense of maximizing each SIR for a given power vector is of the form

$$I_k(\mathbf{p}) = \min_{\mathbf{u} \in \mathcal{U}} \varrho_k(\mathbf{p}, \mathbf{u}), \quad k \in \mathcal{K}. \quad (3)$$

It may be verified that this interference function satisfies the axioms of Definition 1 as well, and therefore is standard.

Other examples of standard interference functions are $\mathbb{R}_+^K \rightarrow \mathbb{R}_+ : \mathbf{p} \mapsto \max_{\xi \in X} \varrho_k(\mathbf{p}, \xi)$ and $\mathbb{R}_+^K \rightarrow \mathbb{R}_+ : \mathbf{p} \mapsto \min_{u \in \mathcal{U}_k} \max_{\xi \in X} \varrho_k(\mathbf{p}, u, \xi)$ where $\varrho_k(\mathbf{p}, \xi)$ and $\varrho_k(\mathbf{p}, u, \xi)$ are standard interference functions of $\mathbf{p}$ for any fixed $\xi \in X$ and $u \in \mathcal{U}_k$. Given a power allocation $\mathbf{p}$, the values $\varrho_k(\mathbf{p}, \xi)$ and $\varrho_k(\mathbf{p}, u, \xi)$ are equal to the interference powers under some interference uncertainty ξ from some (suitable) compact set X . The interference uncertainty means here that the interference power continuously varies depending on the choice of $\xi \in X$. Thus, interference functions of this form can be used, for instance, to model the worst-case interference under imperfect channel knowledge [38].

Let $I(\mathbf{p}) = (I_1(\mathbf{p}), \dots, I_K(\mathbf{p}))$. This vector-valued interference function is referred to as standard if I_k for each k is a standard interference function. The following proposition, whose proof is omitted for lack of space, is an extension of the result presented in [4] to nonnegative power vectors.

Proposition 1: Let $I : \mathbb{R}_+^K \rightarrow \mathbb{R}_{++}^K$ be a standard interference function. Then, I is component-wise continuous.

Let $\gamma_k > 0$ be the SIR target of user k in the sense that this user is satisfied with the quality-of-service provided by the network if $\text{SIR}_k(\mathbf{p}) \geq \gamma_k$ for some power vector $\mathbf{p}$. If this holds for every user, then the power allocation is also said to be valid. Now, considering Definition 1 and Proposition 1, it follows that $\mathbf{\Gamma} = \text{diag}(\gamma_1, \dots, \gamma_K)$ is feasible if and only if

$$0 < C(\mathbf{\Gamma}) := \inf_{\mathbf{p} > 0} \max_{k \in \mathcal{K}} \frac{\gamma_k I_k(\mathbf{p})}{p_k} < 1. \quad (4)$$

Note that the infimum cannot be attained due to the axiom A2 but, by the axiom A1, it must be larger than 0.

By [3], we know that if $C(\Gamma) < 1$, then there exists a unique power vector $\mathbf{p}^* > 0$ such that

$$\mathbf{p}^* = \mathcal{I}(\mathbf{p}^*) \quad (5)$$

where and hereafter (for brevity) we use $\mathcal{I}(\mathbf{p}) := (\mathcal{I}_1(\mathbf{p}), \dots, \mathcal{I}_K(\mathbf{p})) = (\gamma_1 I_1(\mathbf{p}), \dots, \gamma_K I_K(\mathbf{p}))$.

Moreover, from [3], we know that the iteration

$$\mathbf{p}(n+1) = \mathcal{I}(\mathbf{p}(n)), \quad n \in \mathbb{N}_0 \quad (6)$$

converges to $\mathbf{p}^*$ given by (5) as $n \rightarrow \infty$, regardless of the choice of $\mathbf{p}(0)$. In other words, if (4) is satisfied, then (6) converges to the unique fixed point of the standard interference function $\mathcal{I}$. Note that the SIR targets are satisfied with equality under the power vector $\mathbf{p}^* > 0$.

III. POWER CONTROL WITH ACTIVE LINK PROTECTION

Let $n \in \mathbb{N}$ be a time index. Given $\{\mathbf{p}(n)\}_{n \in \mathbb{N}} = \{(p_1(n), \dots, p_K(n))\}_{n \in \mathbb{N}}$, a sequence of power vectors, we use $\text{SIR}_k(n) := \text{SIR}_k(\mathbf{p}(n))$ to denote the SIR of user k at time n . Let $\mathcal{A}_n = \{k \in \mathcal{K} : \text{SIR}_k(n) \geq \gamma_k\}$ be the index set of users that satisfy their SIR targets at time n . Furthermore, we define $\mathcal{B}_n = \mathcal{K} \setminus \mathcal{A}_n$. We say that user k is active at time n if $k \in \mathcal{A}_n$. Otherwise, it is said to be inactive. Each inactive user aims at becoming an active one. Without loss of generality, it is assumed that $\mathcal{A}_n = \{1, \dots, M_n\}$ and $\mathcal{B}_n = \{M_n + 1, \dots, K\}$ for some $1 \leq M_n \leq K$. Occasionally, we need the following definition $\bar{\mathcal{B}}_n := \mathcal{B}_n - |\mathcal{A}_n| = \{1, \dots, K - M_n\}$.

We consider the following admission control algorithm with active link protection (ALP) for power-controlled networks [1]:

$$p_k(n+1) = \begin{cases} \delta \gamma_k I_k(\mathbf{p}(n)) & k \in \mathcal{A}_n \\ \delta p_k(n) = \delta^{n+1} p_k(0) & k \in \mathcal{B}_n \end{cases} \quad (7)$$

where $\delta \in (1, \infty)$ is some given constant, $\mathcal{A}_0 \neq \emptyset$ (at least one user is assumed to be admitted at the beginning since otherwise we have a classical power control problem) and I_k is any standard interference function (according to Definition 1) and $p_k(0) > 0$ is arbitrary for each $k \in \mathcal{B}_0$. Note that (7) is called an admission control algorithm as all users in $\mathcal{B}_n$ are seeking admission to

the network. As $k \in \mathcal{A}_n$ if and only if $p_k(n) \geq \gamma_k I_k(\mathbf{p}(n))$, the iteration (7) can be equivalently written as

$$\mathbf{p}(n+1) = \delta \mathbf{T}(\mathbf{p}(n)) \quad (8)$$

where $\mathbf{T} = (T_1, \dots, T_K) : \mathbb{R}_+^K \rightarrow \mathbb{R}_+^K$ is given by

$$T_k(\mathbf{p}) = \min\{p_k, \gamma_k I_k(\mathbf{p})\} = \min\{p_k, \mathcal{I}_k(\mathbf{p})\}. \quad (9)$$

We point out that unless $\mathcal{B}_n = \emptyset$, $\mathbf{T}$ is not a standard interference function as the axioms A1 and A2 are not satisfied. Thus, the convergence of (7) and (8) does not follow from [3] (note that in [3], the corresponding interference functions are made standard by adding an arbitrarily small positive vector to the power vector).

Throughout the paper, we use $\mathbf{p}^{(a)}(n)$ and $\mathbf{p}^{(i)}(n)$ to denote the power vectors of the active and inactive users at time n , respectively. Hence, $\mathbf{p}(n) = (\mathbf{p}^{(a)}(n), \mathbf{p}^{(i)}(n))$ and, if the time index n can be dropped, we have $\mathbf{p} = (\mathbf{p}^{(a)}, \mathbf{p}^{(i)})$. Moreover, $\mathcal{I}_n^{(a)} : \mathbb{R}_+^K \rightarrow \mathbb{R}_+^{|\mathcal{A}_n|}$ and $\mathcal{I}_n^{(i)} : \mathbb{R}_+^K \rightarrow \mathbb{R}_+^{|\mathcal{B}_n|}$ are used to denote the corresponding interference functions. Consequently, $\mathcal{I}_n(\mathbf{p}) = (\mathcal{I}_n^{(a)}(\mathbf{p}), \mathcal{I}_n^{(i)}(\mathbf{p}))$ and $\mathcal{I}(\mathbf{p}) = (\mathcal{I}^{(a)}(\mathbf{p}), \mathcal{I}^{(i)}(\mathbf{p}))$. It is important to notice that $\mathcal{I}_n \neq \mathbf{T}$, unless $\mathcal{B}_n = \emptyset$ or, equivalently, unless all users are admitted to the network. Following [1], we differentiate between the three cases:

- (C.1) $C(\mathbf{\Gamma}) < C(\delta \mathbf{\Gamma}) < 1$: The users seeking admission to the network (inactive users) are fully admissible.
- (C.2) $C(\mathbf{\Gamma}) < 1$ and $C(\delta \mathbf{\Gamma}) \geq 1$: The inactive users are fully admissible but δ -incompatible.
- (C.3) $C(\mathbf{\Gamma}) \geq 1$: The inactive users are not fully admissible or, using the terminology of [1], *totally inadmissible*.

A. Some properties of the control scheme

Now, we prove interesting properties of the scheme. Throughout this subsection, we need the following lemma.

Lemma 1: Let $\delta > 1$ be arbitrary. For any $n \in \mathbb{N}_0$ and $k \in \mathcal{K}$, we have $I_k(\mathbf{p}(n+1)) < \delta I_k(\mathbf{p}(n))$.

Proof: Let $n \in \mathbb{N}_0$ be arbitrary. As $p_k(n) \geq \gamma_k I_k(\mathbf{p}(n))$ for any $k \in \mathcal{A}_n$, it follows from the definition of $\mathbf{T}$ in (9) that $\mathbf{T}(\mathbf{p}(n)) \leq \mathbf{p}(n)$. So, by A2 and A3, this implies that

$$I_k(\mathbf{p}(n+1)) = I_k(\delta \mathbf{T}(\mathbf{p}(n))) < \delta I_k(\mathbf{T}(\mathbf{p}(n))) \leq \delta I_k(\mathbf{p}(n)), \quad k \in \mathcal{K}.$$

The proof is complete. ■

Now we use the lemma to show an important property of the algorithm, namely the *protection of active users* or, in short, ALP. This property was already reported in [3, Theorem 10].

Proposition 2: Let $\delta > 1$. Then, $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}, n \in \mathbb{N}_0$.

Proof: Let $n \in \mathbb{N}_0$ and $k \in \mathcal{A}_n$ be arbitrary. Since we have $p_k(n+1) = \delta \gamma_k I_k(\mathbf{p}(n))$, Lemma 1 implies that

$$\text{SIR}_k(\mathbf{p}(n+1)) = \frac{p_k(n+1)}{I_k(\mathbf{p}(n+1))} > \frac{\delta \gamma_k I_k(\mathbf{p}(n))}{\delta I_k(\mathbf{p}(n))} = \gamma_k.$$

Thus, $k \in \mathcal{A}_{n+1}$, which completes the proof. ■

Note that the proposition holds even if $C(\Gamma) \geq 1$, that is, even if the inactive users are totally inadmissible. In other words, the users seeking admission to the network under the considered strategy do not destroy the connections of the active users in the sense that the SIR targets of these users remain satisfied. This protection is achieved at the cost of increased transmit powers of the active users. The increase of power in every iteration step is however bounded above by δ . Indeed, for any $k \in \mathcal{A}_n$ and $n \in \mathbb{N}$, one has

$$p_k(n+1)/p_k(n) < \delta. \quad (10)$$

This is because if $k \in \mathcal{A}_n$, then $p_k(n) \geq \gamma_k I_k(\mathbf{p}(n))$, and hence $p_k(n+1) = \delta \gamma_k I_k(\mathbf{p}(n)) \leq \delta p_k(n)$. Moreover, by the proof of Proposition 2, strict inequality holds yielding (10). The next proposition shows that the SIRs of inactive users increases under the power control iteration (7).

Proposition 3: Let $\delta > 1$ and $k \in \mathcal{B}_n \neq \emptyset$ be arbitrary. Then, for every $n \in \mathbb{N}$, $\text{SIR}_k(\mathbf{p}(n)) < \text{SIR}_k(\mathbf{p}(n+1))$.

Proof: Let $k \in \mathcal{B}_n$ and $n \in \mathbb{N}_0$ be arbitrary. Then,

$$\text{SIR}_k(\mathbf{p}(n+1)) = \frac{p_k(n+1)}{I_k(\mathbf{p}(n+1))} = \frac{\delta p_k(n)}{I_k(\mathbf{p}(n+1))}.$$

By Lemma 1, we have $I_k(\mathbf{p}(n+1)) < \delta I_k(\mathbf{p}(n))$. Consequently, $\text{SIR}_k(\mathbf{p}(n+1)) > \text{SIR}_k(\mathbf{p}(n))$. ■

Again, we point out that the proposition holds regardless of whether the inactive users are fully admissible or not. Note that the algorithm generates a *strictly* increasing sequence of SIRs for each user seeking admission to the network. As a result, an inactive user either becomes an active one or its SIR converges to some value $\bar{\text{SIR}}_k < \gamma_k$ (due to the boundedness and strict increasingness of the sequence).

In the remainder of this section, we assume the following additional condition on interference functions.

(C.4) If $\mathcal{B}_n \neq \emptyset$ for some $n \in \mathbb{N}_0$, then, for each $k \in \mathcal{A}_n$, there is $l \in \mathcal{B}_n$ such that I_k is strictly increasing in p_l .

The above condition means that no active user is orthogonal to all inactive users. Thus, we exclude the trivial cases when the inactive users have no impact on active ones.

Lemma 2: For each $k \in \mathcal{K}$, we have $\lim_{c \rightarrow \infty} \mathcal{I}_k(c\mathbf{p})/c = \mathcal{J}_k(\mathbf{p})$, $\mathbf{p} \geq 0$, for some function $\mathcal{J}_k : \mathbb{R}_+^K \rightarrow \mathbb{R}_+$ satisfying each of the following:

- $\tilde{A}1$ $\mathcal{J}_k(\mathbf{p}) \geq 0$ (nonnegativity).
- $\tilde{A}2$ $\mathcal{J}_k(\mu\mathbf{p}) = \mu\mathcal{J}_k(\mathbf{p})$ for all $\mu > 0$ (homogeneity).
- $\tilde{A}3$ $\mathcal{J}_k(\mathbf{p}^{(1)}) \geq \mathcal{J}_k(\mathbf{p}^{(2)})$ if $\mathbf{p}^{(1)} \geq \mathbf{p}^{(2)}$ (monotonicity).

Proof: The proof can be found in App. VI-A. ■

The Lemma 2 states that $\mathcal{I}_k(c\mathbf{p})/c$ converges to a general interference function [4] as c tends to infinity. In particular, for the linear interference function (1) and the minimum interference function (3) this is in accordance with the intuition that the additive background noise can be neglected if the power vector is scaled to infinity. An important consequence of the lemma is the fact that the function $\mathcal{J}_k(\mathbf{p}) = \lim_{c \rightarrow \infty} \mathcal{I}_k(c\mathbf{p})/c$ is continuous for $\mathbf{p} > 0$ [4, Sect. 2.1.2]. Note that assuming a strictly positive power vector $\mathbf{p}$ does not restrict generality as by $A1$ and (7) we have $p_k(n) > 0$ for all $k \in \mathcal{K}$ and $n > 0$.

Lemma 3: If (C.4) holds, $\mathcal{J}_k((\mathbf{p}^{(a)}, \mathbf{p}^{(i)}))$, $k \in \mathcal{A}$, is a standard interference function of $\mathbf{p}^{(a)} \geq 0$ for any fixed $\mathbf{p}^{(i)} > 0$.

Proof: $A3$ of Definition 1 follows directly from $\tilde{A}3$. Positivity $A1$ is due to (C.4) and the fact that $\mathbf{p}^{(i)}$ is positive. Indeed, if there was $\mathbf{p} = (\mathbf{p}^{(a)}, \mathbf{p}^{(i)}) \geq 0$ with $\mathbf{p}^{(i)} > 0$ such that $\mathcal{J}_k(\mathbf{p}) = 0$, then, by (C.4), we would obtain $\mathcal{J}_k(\mu\mathbf{p}) < 0$ for any $\mu \in (0, 1)$, which would contradict $\tilde{A}1$. Scalability $A2$ is a consequence of $\tilde{A}2$ and (C.4): For any $\mu > 1$, we have $\mathcal{J}_k((\mu\mathbf{p}^{(a)}, \mathbf{p}^{(i)})) = \mathcal{J}_k(\mu(\mathbf{p}^{(a)}, 1/\mu\mathbf{p}^{(i)})) = \mu\mathcal{J}_k((\mathbf{p}^{(a)}, 1/\mu\mathbf{p}^{(i)})) < \mu\mathcal{J}_k((\mathbf{p}^{(a)}, \mathbf{p}^{(i)}))$ where the last step is due to (C.4) and $\mu > 1$. ■

It is pointed out that Lemma 3 can be easily deduced from [39]. Now we use Lemmas 2 and 3 to prove the following result.

Proposition 4: Suppose that (C.3) and (C.4) hold. Let $\mathcal{A} = \cup_{n \in \mathbb{N}_0} \mathcal{A}_n$, $\mathcal{B} = \cap_{n \in \mathbb{N}_0} \mathcal{B}_n \neq \emptyset$, and

$$\mathcal{J}^{(a)}(\mathbf{p}) := (\mathcal{J}_k(\mathbf{p}))_{k \in \mathcal{A}} \quad \text{with} \quad \mathcal{J}_k(\mathbf{p}) = \lim_{c \rightarrow \infty} \mathcal{I}_k(c\mathbf{p})/c.$$

Then, as $n \rightarrow \infty$, $\text{SIR}_k(n) \rightarrow \bar{\text{SIR}}_k \in (0, \infty)$ and $p_k(n)/\delta^n \rightarrow \bar{p}_k \in (0, \infty)$. If $k \in \mathcal{B}$, then $\bar{p}_k = p_k(0) > 0$. In contrast, for each $k \in \mathcal{A}$, we have

$$\bar{\text{SIR}}_k = \frac{\gamma_k \bar{p}_k}{\mathcal{J}_k(\bar{\mathbf{p}})} = \frac{\gamma_k \bar{p}_k}{\mathcal{J}_k((\bar{\mathbf{p}}^{(a)}, \mathbf{p}^{(i)}(0)))} = \gamma_k, k \in \mathcal{A}$$

where $\mathbf{p}^{(i)}(0) = (p_k(0))_{k \in \mathcal{B}} > 0$ and $\bar{\mathbf{p}}^{(a)} = (\bar{p}_k)_{k \in \mathcal{A}}$ satisfies $\bar{\mathbf{p}}^{(a)} = \mathcal{J}^{(a)}((\bar{\mathbf{p}}^{(a)}, \mathbf{p}^{(i)}(0)))$.

Proof: The proof is deferred to Appendix VI-B. ■

Now we replace the condition of total inadmissibility (C.3) by full admissibility (C.1) to show that the algorithm (7) does what it was designed to do.

Proposition 5: Suppose that (C.1) and (C.4) hold. Then, there is a finite $n_0 \in \mathbb{N}$ so that $\mathcal{A}_{n_0} = \mathcal{K}$. Moreover, as $n \rightarrow \infty$, we have $p_k(n) \rightarrow \bar{p}_k = \delta \gamma_k I_k(\bar{\mathbf{p}}) = \delta \mathcal{I}_k(\bar{\mathbf{p}})$, $k \in \mathcal{K}$.

Proof: The reader can find the proof in Appendix VI-C. ■

The last result considers the case (C.2).

Proposition 6: Let (C.2), 2 and (C.4) be satisfied. Then, there is a finite $n_0 \in \mathbb{N}$ so that $\mathcal{A}_n = \mathcal{K}$ for all $n \geq n_0$. However, $p_k(n) \rightarrow \infty$ for each $k \in \mathcal{K}$ as $n \rightarrow \infty$.

Proof: Since $C(\Gamma) < 1$ is a necessary and sufficient condition for the existence of a unique fixed point $\bar{\mathbf{p}} > 0$ such that $\bar{\mathbf{p}} = \mathcal{I}(\bar{\mathbf{p}})$, an admission of all users to the network follows from Proposition 5. However, once all the users are admitted, it follows from [3] and that fact that the SIR targets $\delta\Gamma$ are not feasible (due to $C(\delta\Gamma) \geq 1$) that the algorithm (7) with $\mathcal{B}_n = \emptyset$ diverges in the sense that each transmit power tends to infinity. ■

IV. INCORPORATING POWER CONSTRAINTS

It is important to emphasize that all the properties and, in particular, the protection of active users (ALP property) have been obtained under the assumption of no constraints on transmit powers. Since the power at which users transmit their signals is always limited, scepticism may arise about the practical value of the results. This section deals with the problem under which additional conditions the results obtained in the previous subsection apply to power-constrained control schemes.

Everything is defined as in the previous section except that $\mathbf{p} \geq 0$ is confined to be a member of some compact, convex and downward-comprehensive set $\mathbf{P} \subset \mathbb{R}_+^K$ with $\mathbf{0} \in \mathbf{P}$, which represents

some power constraints. The algorithm (7) or, equivalently, (8) with (9) must be modified to take into account these power constraints. This modification may involve the inclusion of projection of power updates on the set P . For simplicity, throughout this section, we assume the individual power constraints on each link so that $P = \{\mathbf{p} \in \mathbb{R}_+^K : \forall_{k \in \mathcal{K}} p_k \leq \hat{p}_k\}$ for some given $\hat{\mathbf{p}} := (\hat{p}_1, \dots, \hat{p}_K) > 0$. In this case, a power-constrained version of (8) is

$$\mathbf{p}(n+1) = \delta \mathbf{T}(\mathbf{p}(n), \hat{\mathbf{p}}/\delta), \mathbf{p}(0) \in \mathbb{R}_{++}^K \quad (11)$$

where $\mathbf{T} : \mathbb{R}_+^K \times \mathbb{R}_{++}^K \rightarrow \mathbb{R}_+^K$ is of the form

$$\mathbf{T}(\mathbf{p}, \hat{\mathbf{p}}) = \min\{\mathbf{p}, \mathcal{I}(\mathbf{p}), \hat{\mathbf{p}}\} \quad (12)$$

where the minimum is taken component-wise.

In the unconstrained case, the notions of admissibility and δ -compatibility play crucial roles for the behavior of the control scheme (see (C.1)–(C.3)). In the presence of power constraints, however, the lack of δ -compatibility has different implications. To see this, note that (4) is necessary but not sufficient for the SIR targets to be feasible under power constraints. A necessary and sufficient condition for feasibility of Γ is that [40]

$$0 < C(\Gamma; P) := \min_{\mathbf{p} \in P} \max_{k \in \mathcal{K}} \frac{\gamma_k I_k(\mathbf{p})}{p_k} \leq 1. \quad (13)$$

Let $\mathbf{p}' \in P$ denote any minimizer in (13) so that

$$\mathbf{p}' := \arg \min_{\mathbf{p} \in P} \max_{k \in \mathcal{K}} \frac{\gamma_k I_k(\mathbf{p})}{p_k}. \quad (14)$$

Obviously, as $P \subset \mathbb{R}_+^K$, we have $C(\Gamma) \leq C(\Gamma; P)$, and thus $C(\Gamma) < 1$ does not necessarily imply $C(\Gamma; P) \leq 1$. In such cases, $C(\Gamma; P)$ defined by (13) provides a basis for defining the notion of admissibility. In analogy to the previous definitions, we can say that the inactive users are

(C.5) fully admissible if $C(\Gamma; P) \leq C(\delta\Gamma; P) \leq 1$,

(C.6) fully admissible but δ -incompatible if $C(\Gamma; P) \leq 1 < C(\delta\Gamma; P)$,

(C.7) totally inadmissible if $C(\Gamma; P) > 1$.

Proposition 7: As $n \rightarrow \infty$, $\text{SIR}_k(n) \rightarrow \bar{\text{SIR}}_k \in (0, \infty)$ and $p_k(n) \rightarrow \bar{p}_k \in (0, \hat{p}_k]$, $k \in \mathcal{K}$, under (11). If (C.5) holds, then $\bar{\mathbf{p}} = \mathbf{p}^\circ$ where $\mathbf{p}^\circ > 0$ is the unique vector satisfying

$$\mathbf{p}^\circ = \delta \mathcal{I}(\mathbf{p}^\circ) \leq \hat{\mathbf{p}}. \quad (15)$$

Proof: The proof is deferred to Appendix VI-D. ■

Thus, the algorithm (11) converges to the fixed point of $\hat{\mathcal{I}}(\mathbf{p}) = \min\{\delta\mathcal{I}(\mathbf{p}), \hat{\mathbf{p}}\}$ (see also the proof of the proposition), which is a valid power allocation provided that (C.5) is fulfilled. This fixed point however is not necessarily a valid power allocation if the users are fully admissible but δ -incompatible ((C.6)), which stands in clear contrast to the unconstrained case. Thus, Condition (C.5) is crucial for the algorithm to be of any value, which also shows that δ should be chosen very carefully. An open question that remains is to what extent the ALP property is preserved under (C.5) when limitations on transmit powers are taken into account. We address this problem in the remainder of this section. From [3], [1], we know that the property of protecting active users does not carry over in its full generality to the power-constrained case.

Considering the modified iteration (11) with (12) shows, together with A2 and A3, that, for every $n \in \mathbb{N}_0$ and $k \in \mathcal{K}$,

$$\begin{aligned} I_k(\mathbf{p}(n+1)) &= I_k(\delta\mathbf{T}(\mathbf{p}(n), \hat{\mathbf{p}}/\delta)) = I_k(\delta \min\{\mathbf{p}(n), \mathcal{I}(\mathbf{p}(n)), \hat{\mathbf{p}}/\delta\}) \\ &< \delta I_k(\min\{\mathbf{p}(n), \mathcal{I}(\mathbf{p}(n)), \hat{\mathbf{p}}/\delta\}). \end{aligned} \quad (16)$$

Consequently, Lemma 1 holds for the power-constrained case as well, and hence, for any $n \in \mathbb{N}_0$ and $k \in \mathcal{A}_n$, one has

$$\text{SIR}_k(\mathbf{p}(n+1)) \geq \frac{\min\{\hat{p}_k, \delta\gamma_k I_k(\mathbf{p}(n))\}}{I_k(\delta \min\{\mathbf{p}(n), \mathcal{I}(\mathbf{p}(n)), \hat{\mathbf{p}}/\delta\})} \quad (17)$$

$$> \frac{\min\{\hat{p}_k, \delta\gamma_k I_k(\mathbf{p}(n))\}}{\delta I_k(\min\{\mathbf{p}(n), \mathcal{I}(\mathbf{p}(n)), \hat{\mathbf{p}}/\delta\})} \quad (18)$$

where in the first step we used the fact that $\delta\gamma_k I_k(\mathbf{p}(n)) \leq \delta p_k(n)$ when user k is active at time n . The following proposition shows a sufficient condition for the protection of active users to hold at all times.

Proposition 8: Let $\delta > 1$, $n \in \mathbb{N}_0$, and $k \in \mathcal{A}_n$ be arbitrary. If $\hat{p}_k \geq \mathcal{I}_k(\hat{\mathbf{p}}) = \gamma_k I_k(\hat{\mathbf{p}})$, then we have $k \in \mathcal{A}_{n+1}$. Thus, if $\hat{\mathbf{p}}$ is a valid power allocation, that is, if

$$\hat{\mathbf{p}} \geq \mathcal{I}(\hat{\mathbf{p}}) \quad (19)$$

then $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$ for all $n \in \mathbb{N}_0$.

Proof: We consider two cases depending on whether the power constraint of an active user at time $n+1$ is violated or not. First assume $\hat{p}_k \geq \delta\gamma_k I_k(\mathbf{p}(n))$. An examination of (18) shows that $\text{SIR}_k(\mathbf{p}(n+1)) > \gamma_k$. Now assuming that $\hat{p}_k < \delta\gamma_k I_k(\mathbf{p}(n))$, $k \in \mathcal{A}_n$, we see from (17)

together with (19) that $\text{SIR}_k(\mathbf{p}(n+1))$ is bounded below by $\hat{p}_k/I_k(\hat{\mathbf{p}})$. This completes the proof. $\blacksquare$

Note that if (C.5) holds, then (19) is implied by $\delta\mathcal{I}(\mathbf{p}') \geq \mathcal{I}(\hat{\mathbf{p}})$, which in turn is satisfied if $\delta\mathbf{p}' \geq \hat{\mathbf{p}}$, where $\mathbf{p}'$ is defined by (14). This is simply because if (C.5) is true, we have $\delta\mathcal{I}(\mathbf{p}') \leq \mathbf{p}' \leq \hat{\mathbf{p}}$. As $\mathbf{p}^\circ \leq \mathbf{p}' \leq \hat{\mathbf{p}}$, it is obvious that $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$ for all $n \in \mathbb{N}_0$ whenever $\delta\mathcal{I}(\mathbf{p}^\circ) \geq \mathcal{I}(\hat{\mathbf{p}})$ or $\delta\mathbf{p}^\circ \geq \hat{\mathbf{p}}$, where $\mathbf{p}^\circ$ is given by (15) and is independent of $\hat{\mathbf{p}}$. All these conditions are more restrictive than (19) but they may be of interest when for instance $I_k(\hat{\mathbf{p}})$ is not known or difficult to determine.

A. Distress Signaling

The foregoing conditions are independent of $n \in \mathbb{N}_0$, and thus, if they are satisfied, the ALP property is guaranteed for all $n \in \mathbb{N}_0$, just as in the case of unconstrained transmit powers. Now the question is what to do when (19) and with it all the consequential conditions, cannot be guaranteed. One possible remedy is to apply the concept of distress signaling where users are prohibited from increasing their transmit powers whenever they receive a distress signal (special tone in a control slot or some separate control channel) broadcasted by at least one active user. The idea was already mentioned in [1] where the distress signal is suggested to be broadcasted when an active user is about to exceed its power limit at some time point, that is, when $\hat{p}_k < \delta\mathcal{I}_k(\mathbf{p}(n))$ for some $k \in \mathcal{K}$ and $n \in \mathbb{N}_0$. One problem with this approach is that the active users may be about to violate their power constraints again and again, thereby generating distress signals at many different time points. In some situations, it would be better not to deactivate the distress signal until it is guaranteed that all the inactive users can be admitted with the protection of active users.

In this subsection, we derive more general conditions under the assumption of standard interference functions. First we slightly strengthen the condition $\delta\mathbf{p}' \geq \hat{\mathbf{p}}$.

Proposition 9: Suppose that (C.5) is satisfied and $\mathbf{p}$ is any power vector such that

$$\delta\mathcal{I}(\mathbf{p}) \leq \mathbf{p} \leq \hat{\mathbf{p}}. \quad (20)$$

Let $\lambda := \lambda(\delta, \mathbf{p})$ be any constant for which $\mathcal{I}(\lambda\delta\mathbf{p}) \leq \hat{\mathbf{p}}$. If

$$\mathbf{p}(m) \leq \lambda\delta\mathbf{p} \quad (21)$$

for some $m \in \mathbb{N}_0$, then $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$ for all $n \geq m$.

Proof: We refer to Appendix VI-E. ■

Any power vector satisfying (20) is called a δ -valid power vector/allocation. Notice that if (C.5) hold, a δ -valid power vector exists. Particular examples of such vectors are $\mathbf{p}'$ and $\mathbf{p}^\circ$ defined by (14) and (15), respectively. Also note that due to A2 and Proposition 1, there exists λ strictly larger than 1.

By Proposition 9, we have the ALP property if the inactive users are totally admissible and the transmit powers are sufficiently small so that (21) is fulfilled. A useful property of this result is that once (21) is satisfied, there is no need to verify this condition again, unless (20) is violated due to, for instance, fading effects or arrival of new inactive users. The main problem with (21), however, is how to efficiently obtain a δ -valid power allocation in a distributed environment. One possibility is to bound below the set of δ -valid power allocations under the worst-case scenario. This problem is left open. Instead we consider the possibility of letting each user compare its transmit power with the interference power. First, we use Proposition 9 to prove the following result.

Proposition 10: Assume (C.5) and let $\lambda \geq 1$ be defined as in Proposition 9. If

$$\frac{\mathbf{p}(m)}{\lambda\delta} \leq \delta\mathcal{I}\left(\frac{\mathbf{p}(m)}{\lambda\delta}\right) \quad (22)$$

for some $m \in \mathbb{N}_0$, then $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$ for all $n \geq m$.

Proof: See Appendix VI-F. ■

Notice that by Proposition 1, A2 and (15), there exists $\lambda > 1$ satisfying the condition of the proposition: $\mathcal{I}(\lambda\delta\mathbf{p}^\circ) \leq \hat{\mathbf{p}}$. Choosing $\lambda = 1$ leads us to the following corollary.

Corollary 1: If (C.5) holds and

$$\mathbf{p}(m) \leq \delta^2\mathcal{I}(\mathbf{p}(m)/\delta) \quad (23)$$

for some $m \in \mathbb{N}_0$, then $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$ for all $n \geq m$.

We point out that it is not clear whether (22), and with it (23), is preserved in general. The results solely show that once (22) or (23) is satisfied, then the ALP property is ensured for all time instances $n \geq m$. It must be also emphasized that (22) and (23) are *less restrictive* than $\mathbf{p}(m) \leq \delta\mathcal{I}(\mathbf{p}(m))$ as $x \mapsto x\mathcal{I}_k(\mathbf{p}/x)$ is strictly increasing for any $\mathbf{p} > 0$ (see also the proof of Proposition 11).

The main problem with Proposition 10 and Corollary 1 is that $\mathcal{I}_k(\mathbf{p}(m)/(\lambda\delta))$ and $\mathcal{I}_k(\mathbf{p}(m)/\delta)$ may be not known to user k at time m even if $\mathcal{I}_k(\mathbf{p}(m))$ is known.³ The following proposition shows that the ALP property is guaranteed even if $\mathbf{p}(m) > \delta\mathcal{I}(\mathbf{p}(m))$, provided that the entries of $\mathbf{p}(m)$ are not too large. In other words, there is always some margin around the value $\delta\mathcal{I}(\mathbf{p}(m))$ so that the protection is guaranteed whenever $\mathbf{p}(m)$ belongs to this margin.

Proposition 11: Suppose that (C.5) is true and

$$\mathbf{p}(m) \leq \beta\delta\mathcal{I}(\mathbf{p}(m)) \quad (24)$$

holds for some $m \in \mathbb{N}_0$ and $\beta \in [1, \beta_{\max}]$. Then, there exists $\beta_{\max} > 1$ such that $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$ for all $n \geq m$.

Proof: See Appendix VI-G. ■

By the proposition, we have the protection of active users for all $n \geq m$ if (24) holds for some sufficiently small $\beta \geq 1$. The main insight is that there is the possibility of choosing β being *strictly* larger than one.

In the remainder of this section, we summarize our findings and make some suggestions as to what to do when (C.5) is not fulfilled. For brevity, we focus on condition (24) but the subsequent discussion also applies to (22) and (23) (with (24) substituted by (22) or (23)). Given some $\beta > 1$ and $\delta > 1$ (both sufficiently small), let $P' \subseteq P$ be the set of all power allocations for which (24) is satisfied. When $\mathbf{p}(n) \notin P'$, the scheme prevents all users from increasing their powers by broadcasting distress signals on a common control channel. The distress signals are sent by all the active users $k \in A_n$ such that $p_k(n) > \beta\delta\mathcal{I}_k(\mathbf{p}(n))$, which can be verified locally. First assume that (C.5) holds, meaning that there is an additional mechanism to ensure full admissibility of all users. Then, the admission control algorithm with distress signaling becomes:

$$\mathbf{p}(n+1) = \begin{cases} \min\{\mathbf{p}(n), \delta\mathcal{I}(\mathbf{p}(n))\} & \mathbf{p}(n) \notin P' \\ \delta\mathbf{T}(\mathbf{p}(n), \hat{\mathbf{p}}/\delta) & \mathbf{p}(n) \in P' \end{cases} \quad (25)$$

where $\mathbf{T}$ is defined by (12). From (25), we see that the admission control algorithm (11) stops if $\mathbf{p}(n) \notin P'$ (at least one active user transmits a distress signal), in which case no user increases its transmit power. Therefore, active users are protected as the interference powers do not increase

³In some cases, e.g. when I_k is a linear interference function (1) and the noise factor is known, the value $\mathcal{I}_k(\mathbf{p}(m)/\delta)$ can be obtained from $\mathcal{I}_k(\mathbf{p}(m))$

and each active user, say user $k \in A_n$, decreases its transmits power if and only if $p_k(n) > \delta \mathcal{I}_k(\mathbf{p}(n))$. Moreover, since the transmit power of user k decreases as long as $p_k(n) > \delta \mathcal{I}_k(\mathbf{p}(n))$ and other transmit powers are kept constant, there must be a time point $m \geq n$ such that $\mathbf{p}(m) \in P'$. Once this condition is satisfied, no distress signal is broadcasted and, by (25), the iteration (11) is resumed. Now the active users are guaranteed to be protected for all $n \geq m$, provided that (C.5) is satisfied.

Now if (C.5) is not satisfied, the problem is open but we have to differentiate between (C.6) and (C.7). In the case of (C.6), the algorithm in (25) applies, provided that the parameter $\delta > 1$ is reduced so as to fulfill (C.5) at the expense of extending the duration of the whole admission process. So the only issue is when and how to reduce δ to provide full admissibility. In contrast, if (C.7) is true, then it is impossible to admit all users at the required quality-of-service, and therefore the SIR target of some active user will be violated at some time point. A simple idea is then to let this active user permanently send a distress signal so that no transmit powers are increased and, after some time point, first inactive users will drop out of the system. Obviously, a better approach would be to let inactive user (cooperatively) estimate $C(\mathbf{\Gamma}; \mathbf{P})$ and $C(\delta \mathbf{\Gamma}; \mathbf{P})$ so that they do not even attempt to access the network if $C(\mathbf{\Gamma}; \mathbf{P}) > 1$. However, an efficient estimation of these quantities in a distributed environment is still an open problem.

We point out that there are two possible interpretations of the admission problem and the scheme (25). The first one is *how* to admit inactive users if we know that they are fully admissible in the sense of (C.5), and the second one is *whether* to admit them to the network when we do not know if they are admissible or not. In the former case, (25) guarantees that the incoming users will be admitted in finite time and the existing ones will be protected. In the latter case, the incoming users will either be admitted (as described above), or the SIR target of some active user will be violated for a single time point, which will prove that the condition (C.5) is not satisfied. Therefore, the considered scheme does not lead to admission errors and the decision is always made within finite time. However, the exact number of iterations of (25) needed to make a decision is not determined. Especially if the SIR targets are close to the maximum supportable SIR targets in the system this number may be high which may lead to noticeable delays.

V. LINEAR TRANSCEIVER OPTIMIZATION

Any user intending to access the network must select its transmit vector by determining, for instance, its beamforming vector. The transmit vectors have different physical meanings, depending on the realization of the physical layer. Abstractly speaking, the transmit vectors determine the “directions” of transmit signals in some appropriately chosen signal space (see also the multiple antenna case below). Note that once the transmit vectors of the inactive users are determined, they cannot be modified arbitrarily as the iteration (7) does not guarantee the protection of active users under such modifications. On the other hand, the transmit vectors of active users may prevent an inactive user from entering the network. Inspired by [5], we alleviate this problem by considering a scheme in which all transmit vectors (and the power vector) are recalculated so as not to deteriorate the SIR performance of the users. During the transmitter side optimization, the execution of the admission control iteration (7) is suspended. Our objective in this section is to show how much performance gains can be expected by optimizing transmit vectors in addition to power control and receiver-side optimization. Note that due to an optimization of transmit vectors, the scheme does not fall within the framework presented in the previous sections.

The basic idea is to carry out an iterative optimization of transmit and receive vectors⁴ in an alternating manner, with receivers and transmitters exchanging their roles. The transmit beamformers are optimized in the *reversed network*, which is the network obtained by reversing the direction of all links and exchanging the roles of transmitters and receivers on each link (with the actual transmit vectors used as receive vectors). We leverage the fact [5] that if any given SIR values are feasible in the primal network, they are also feasible in the reversed network (albeit with a different power allocation). Every iteration of the algorithm consists of two steps in the primal network and two steps in the reversed network. These two steps to be performed in each network are receive beamformer optimization and power vector computation. Given fixed transmit beamformers and power allocation, the receiver-side optimization in the sense of (3) can be performed in a distributed manner using either pilot-based or blind estimation methods [41]. The power allocations in the primal network can be computed in a decentralized manner using

⁴For instance, the reader can think of transmit and receive vectors as transmit and receive beamformers, respectively. Notice that there is no more than one data stream per link.




Fig. 1: The horizontal axis in both figures represents the iterations, and the legend below the axis provides the information whether these are the iterations of: A - admission and power control (7), or T - transceiver optimization.

the distributed asynchronous on-line power control algorithm of [2], [3] with the SIR values from the reversed network treated as the SIR targets. The power allocation for the reversed network can be computed in the same fashion with the SIR values from the primal network. For more details about the considered transceiver optimization scheme the reader is referred to [42].

The transceiver optimization scheme discussed in this section is supposed to be performed on a regular basis (periodically) or only when necessary. The distributed implementation of the entire scheme, consisting of admission/power control and transceiver optimization, is more challenging compared to the pure admission control scheme presented in Sections III-IV. Previously, only local interference measurements and a common signaling channel to broadcast distress signals were required; now, the users are supposed to be willing to suspend their normal operation and coordinately agree to enter a different operation mode in which they jointly optimize transmit powers and beamformers. However, due to potentially very high performance gains (see simulations in the next section) it seems encouraging to consider at least some reduced form of transceiver optimization in future research.




Fig. 2: Selected optimization phases

A. Simulations

We assume a wireless network with $K = 10$ users and without power constraints, in which the receivers and transmitters are equipped with $n_R = 4$ and $n_T = 4$ antennas, respectively. The wireless channel is assumed to be flat and fixed, with the complex-valued channel coefficients on each link being realizations of i.i.d. circular symmetric normal distributed random variables with zero mean and unit variance. For brevity, there is a common SIR target for all users $\gamma = 8$. Five users are already admitted at time 0 with their SIRs equal to $\delta\gamma = 9.6$, and their transmit and receive beamformers are already pre-optimized (a number of iterations of the transceiver optimization algorithm were performed for those five users). The remaining five users are inactive at time 0 and transmit at some low power. The transmit and receive beamformers of the inactive users were initialized according to the singular value decomposition (SVD) of the corresponding channel matrices.

Figures 1a and 1b present simulation results of a wireless network, in which both admission

control (7) and transceiver optimization are carried out. The evolution of the SIRs of the individual users is presented in Fig. 1a, whereas Fig. 1b depicts the corresponding transmit powers. For a better readability of the plots, four representative users were selected: two initially inactive ones and two initially active ones (shown with solid and with dashed lines, respectively). The curves for the remaining six users are not shown, they evolve however in a similar way to the presented ones. The simulation was configured to start with the admission control scheme (7), which was executed until the SIRs of the users converged (with some given accuracy) or until transmit powers exceeded a given level. Subsequently, the transceiver optimization was performed (for a fixed number of 10 iterations). Then the execution of admission control was resumed; this cycle was repeated 5 times, and in the 6-th, final cycle, only admission control was performed.

Figure 2 presents selected phases of the optimization in more detail. In particular, Fig. 2a shows the first admission control phase. As mentioned above, the transceivers of the initially active users were pre-optimized, but those of the inactive users were not. This leads to high interference for the inactive users, and in consequence none of them achieves the SIR target and can be admitted to the network in this phase, although the transmit powers tend to grow to infinity. It can be however seen that the SIRs of the initially active users do not drop below the target value. Afterwards, the transceiver optimization scheme is performed (phase T.1). The subsequent admission control phase (A.2) is depicted in Fig 2b. We see that one of the previously inactive users can be admitted, but the other one still remains below the SIR target. Thus, this phase (as well as phase A.1) corresponds to the case (C.3) where the users are fully inadmissible. Then, there follows again a transceiver optimization phase. This phase (T.2) is presented in more detail in Fig. 2e. The SIRs of all users are increasing, and it can be observed that the transmit powers do not have the tendency to fast (geometrical) growth. In the following admission control phase A.3 (Fig. 2c), the remaining inactive user is eventually admitted to the network. The transmit powers still tend to grow to infinity, though, and the SIRs converge to γ instead of $\delta\gamma$. This indicates that the users are fully admissible, but δ -incompatible (case (C.2)). However, after another transceiver optimization T.3 is performed, users finally become both fully admissible and δ -compatible (case (C.1)). This is presented in Fig. 2d - the SIRs converge to $\delta\gamma$ and transmit powers to some constant values (as opposed to growing to infinity in the previous phases). The transceiver optimization performed in the following two cycles (T.4 and T.5) leads

to significantly lowering the maximum transmit power. It should be also noted that transmit powers in the final phase converge to much lower values than during the intermediate phases.

In the presented simulation, all 10 users were able to reach the common SIR target $\gamma = 8$. Extensive simulations have shown that at least the SIR target of 24 can be achieved with finite powers, provided that a sufficiently high number of transceiver optimization phases is performed. For comparison, with no optimization of the transmitters, but with optimal receive beamformers, the highest observed common SIR target attained by all users was approximately 1.37, and when both transmit and receive beamformers were fixed and equal to the SVD vectors, the highest feasible SIR target is 0.88. These observations indicate a potential for significant performance gains of the transmitter side optimization.

VI. APPENDIX

A. Proof of Lemma 2

Let $\mathbf{p} \geq 0$ and $k \in \mathcal{K}$ be arbitrary. By A1, $\mathcal{I}_k(c\mathbf{p})/c$ is positive, and hence bounded below by 0 for all $c > 0$. Moreover, A2 implies that $\mathcal{I}_k(c_1\mathbf{p})/c_1 = (c_2/c_1) \mathcal{I}_k(c_1\mathbf{p})/c_1 > \mathcal{I}_k(c_2c_1/c_1\mathbf{p})/c_2 = \mathcal{I}_k(c_2\mathbf{p})/c_2$ for any $0 < c_1 < c_2$. Thus, $\mathcal{J}_k(\mathbf{p}) = \lim_{c \rightarrow \infty} \mathcal{I}_k(c\mathbf{p})/c$ exists and is nonnegative. This proves the existence of $\mathcal{J}_k$ and $\tilde{A}1$. The homogeneity property $\tilde{A}2$ holds since, for any $\mu > 0$, one has $\mathcal{J}_k(\mu\mathbf{p}) = \lim_{c \rightarrow \infty} \mathcal{I}_k(c\mu\mathbf{p})/c = \lim_{c \rightarrow \infty} \mu \mathcal{I}_k(c\mathbf{p})/(\mu c) = \mu \lim_{c' \rightarrow \infty} \mathcal{I}_k(c'\mathbf{p})/c' = \mu \mathcal{J}_k(\mathbf{p})$. Finally, by A3, for any $\mathbf{p}^{(1)} \geq \mathbf{p}^{(2)} \geq 0$ and $c > 0$, we have $0 \leq \mathcal{I}_k(c\mathbf{p}^{(1)})/c - \mathcal{I}_k(c\mathbf{p}^{(2)})/c$. So, $0 \leq \lim_{c \rightarrow \infty} (\mathcal{I}_k(c\mathbf{p}^{(1)})/c - \mathcal{I}_k(c\mathbf{p}^{(2)})/c) = \mathcal{J}_k(\mathbf{p}^{(1)}) - \mathcal{J}_k(\mathbf{p}^{(2)})$, from which $\tilde{A}3$ follows.

B. Proof of Proposition 4

By (C.3), the network is totally inadmissible so that $\mathcal{B} \neq \emptyset$. By Proposition 3, we have $\text{SIR}_k(n) < \text{SIR}_k(n+1)$ for each $k \in \mathcal{B}_n$. As a consequence, there must be a (sufficiently large) number N such that $\mathcal{B} = \mathcal{B}_n \neq \emptyset$ and $\mathcal{A} = \mathcal{A}_n \neq \emptyset$ for all $n \geq N$. Note that $\mathcal{A} \cap \mathcal{B} = \emptyset$. Unless otherwise stated, assume that $n \geq N$. Since $p_k(n+1) = \delta^{n+1}p_k(0)$ for each $k \in \mathcal{B}$, we trivially obtain $p_k(n)/\delta^n = p_k(0) = \bar{p}_k$, $k \in \mathcal{B}$, for all $n \in \mathbb{N}_0$. Moreover, as the sequence $\{\text{SIR}_k(n)\}_{n \geq N}$ is strictly increasing (Proposition 3) and bounded above by γ_k , $k \in \mathcal{B}$, it must converge to some $\bar{\text{SIR}}_k \leq \gamma_k$. Now let us consider the transmit powers of the active users.

Defining $\lambda = \mathbf{p}^{(i)}(0) > 0$, we have

$$\begin{aligned}\mathbf{p}^{(a)}(n+1) &= \delta \mathcal{I}^{(a)}(\mathbf{p}(n)) = \delta \mathcal{I}^{(a)}\left(\left(\mathbf{p}^{(a)}(n), \mathbf{p}^{(i)}(n)\right)\right) = \delta \mathcal{I}^{(a)}\left(\left(\mathbf{p}^{(a)}(n), \delta^n \lambda\right)\right) \\ &= \delta \mathcal{I}^{(a)}\left(\delta^n \left(\frac{1}{\delta^n} \mathbf{p}^{(a)}(n), \lambda\right)\right).\end{aligned}$$

Thus, using $\pi(n) = \mathbf{p}^{(a)}(n)/\delta^n, n \geq N$, we can write

$$\pi(n+1) = \mathcal{I}^{(a)}\left(\delta^n \left(\pi(n), \lambda\right)\right) / \delta^n, \quad n \geq N. \quad (26)$$

Now suppose that $\{\pi(n)\}_{n \geq N}$ is a sequence generated by (26). Thus, since $\text{SIR}_k(n) = \frac{\gamma_k p_k(n)/\delta^n}{\mathcal{I}_k(\mathbf{p}(n))/\delta^n}$, $k \in \mathcal{A}$, the SIR of user $k \in \mathcal{A}$ evolves according to

$$\text{SIR}_k(n) = \frac{\gamma_k (\pi(n))_k}{(\mathcal{I}^{(a)}(\delta^n(\pi(n), \lambda))/\delta^n)_k} \geq \gamma_k, \quad n \geq N$$

where the inequality follows from Proposition 2. Hence, considering Lemma 2 yields (for all $n \geq N$)

$$\pi(n) \geq \mathcal{I}^{(a)}(\delta^n(\pi(n), \lambda))/\delta^n > \mathcal{J}^{(a)}((\pi(n), \lambda)). \quad (27)$$

By Lemma 3, $\mathcal{J}^{(a)}((\pi, \lambda))$ is a standard interference function of π . Thus, by [3], the function has a unique fixed point $\pi^* = \mathcal{J}^{(a)}((\pi^*, \lambda)) > 0$ such that $\pi^* \leq \pi$ for any $\pi \geq \mathcal{J}^{(a)}((\pi, \lambda))$. So, from (27) and A3, we have $\mathcal{I}^{(a)}(\delta^n(\pi(n), \lambda))/\delta^n > \mathcal{J}^{(a)}((\pi^*, \lambda))$, which implies that

$$\gamma_k \leq \text{SIR}_k(n) < \frac{\gamma_k (\pi(n))_k}{(\mathcal{J}^{(a)}((\pi^*, \lambda)))_k}, \quad n \geq N, k \in \mathcal{A}. \quad (28)$$

Moreover, we have $\pi(n) > \pi^* = \mathcal{J}^{(a)}((\pi^*, \lambda)) > 0$ and $\pi(n) < \mathbf{p}^{(a)}(0)$, where the last inequality is an immediate consequence of (10). Thus, the entries of $(\pi(n), \lambda)$ are bounded and bounded away from zero. This together with Lemma 2 implies that, for each $k \in \mathcal{A}$ and any $\epsilon > 0$, there is (a sufficiently large) $M_k \geq N$ such that $1 \leq (\mathcal{I}_k(\delta^n(\pi(n), \lambda))/\delta^n)/\mathcal{J}_k((\pi(n), \lambda)) < 1 + \epsilon$ for all $n \geq M_k$. So, by (26), there is $M = \max_k M_k \geq N$ such that

$$1 \leq \max_{k \in \mathcal{A}} \frac{(\pi(n+1))_k}{\mathcal{J}_k((\pi(n), \lambda))} < 1 + \epsilon, \quad n \geq M.$$

Now letting $\epsilon \rightarrow 0$ ($n \rightarrow \infty$) shows that the sequence $\{\pi(n)\}$ generated by (26) converges to $\pi^* = \mathcal{J}^{(a)}((\pi^*, \lambda))$. Thus, from (28), we obtain (as $n \rightarrow \infty$)

$$\text{SIR}_k(n) = \frac{\gamma_k (\pi(n))_k}{(\mathcal{I}^{(a)}(\delta^n(\pi(n), \lambda))/\delta^n)_k} \rightarrow \frac{\gamma_k \bar{p}_k}{\bar{p}_k} = \gamma_k, \quad k \in \mathcal{A}$$

where $\bar{p}_k = \lim_{n \rightarrow \infty} p_k(n)/\delta^n = (\pi^*)_k = \mathcal{J}_k((\pi^*, \lambda))$.

C. Proof of Proposition 5

Let $\mathcal{A} \neq \emptyset$ and $\mathcal{B}$ be defined as in Proposition 4. The first part is proven by contradiction, and hence assume that there exists $\mathbf{p}(0)$ for which $\mathcal{B} \neq \emptyset$. Thus, by Proposition 4, as $n \rightarrow \infty$,

$$\begin{aligned} \mathbf{p}^{(a)}(n)/\delta^n &\rightarrow \pi^* = \mathcal{J}^{(a)}((\pi^*, \lambda)) & \pi^* &= \bar{\mathbf{p}}^{(a)} \\ \mathbf{p}^{(i)}(n)/\delta^n &= \lambda \leq \mathcal{J}^{(i)}((\pi^*, \lambda)) & \lambda &= \mathbf{p}^{(i)}(0) \end{aligned} \quad (29)$$

where $\mathcal{J}^{(i)}$ is the (vector-valued) interference function corresponding to the inactive users. On the other hand, due to (C.1), we know from [3] that there exists $\mathbf{q} = (\mathbf{q}^{(a)}, \mathbf{q}^{(i)}) > 0$ such that $\mathbf{q} = \mathcal{I}(\mathbf{q}) > \mathcal{J}(\mathbf{q})$ where the last inequality is due to 2. Furthermore, using $\tilde{A}2$ we have $\mu\mathbf{q} > \mathcal{J}(\mu\mathbf{q})$ for any $\mu > 0$, and thus

$$\begin{aligned} \mu\mathbf{q}^{(a)} &> \mathcal{J}^{(a)}((\mu\mathbf{q}^{(a)}, \mu\mathbf{q}^{(i)})) \\ \mu\mathbf{q}^{(i)} &> \mathcal{J}^{(i)}((\mu\mathbf{q}^{(a)}, \mu\mathbf{q}^{(i)})). \end{aligned} \quad (30)$$

Since $\mathbf{q}^{(i)} > 0$ and $\mathbf{p}^{(i)} > 0$, we can always choose the scaling factor $\mu > 0$ such that $\lambda \leq \mu\mathbf{q}^{(i)}$ with $\mu q_l^{(i)} = \lambda_l$ for some index l . So, with (C.4), (30) and our choice of μ , we have

$$\mathcal{J}^{(a)}((\mu\mathbf{q}^{(a)}, \lambda)) \leq \mathcal{J}^{(a)}((\mu\mathbf{q}^{(a)}, \mu\mathbf{q}^{(i)})) < \mu\mathbf{q}^{(a)}.$$

As $\mathcal{J}^{(a)}$ is a standard interference function (Lemma 3), π^* is a *unique* fixed point (given λ) for which $\pi^* \leq \pi$ whenever $\mathcal{J}^{(a)}((\pi, \lambda)) \leq \pi$. Thus, the above inequality together with $\tilde{A}3$ and (29) implies that

$$\pi^* = \mathcal{J}^{(a)}((\pi^*, \lambda)) \leq \mathcal{J}^{(a)}((\mu\mathbf{q}^{(a)}, \lambda)) < \mu\mathbf{q}^{(a)}.$$

Hence, $\pi^* < \mu\mathbf{q}^{(a)}$. Combining this with (29), (30) and $\tilde{A}3$ yields (for an index l such that $q_l^{(i)} = \lambda_l$)

$$\lambda_l \leq \mathcal{J}_l^{(i)}((\pi^*, \lambda)) \leq \mathcal{J}_l^{(i)}((\mu\mathbf{q}^{(a)}, \lambda)) \leq \mathcal{J}_l^{(i)}((\mu\mathbf{q}^{(a)}, \mu\mathbf{q}^{(i)})) < \mu q_l^{(i)} = \lambda_l$$

which is a contradiction. As a result, all users are admitted at some time point n_0 and $\mathcal{B}_n = \emptyset$ for all $n \geq n_0$. If all users are admitted, the algorithm (7) becomes a pure fixed-point power control algorithm, and therefore, by (C.1) and [3], the power vector converges to $\bar{\mathbf{p}} = \delta\mathcal{I}(\bar{\mathbf{p}})$.

D. Proof of Proposition 7

First we prove the following auxiliary result.

Lemma 4: Consider iteration (11). For each $k \in \mathcal{K}$, there exists $n_0(k)$ such that for all $n \geq n_0(k)$ there holds:

$$p_k(n+1) = \min\{\hat{p}_k, \delta\mathcal{I}_k(\mathbf{p}(n))\}. \quad (31)$$

Proof: The lemma is proven by induction. Note that there exists $n = n_0(k)$ so that

$$\begin{aligned} p_k(n_0(k)+1) &= \delta(\mathbf{T}(\mathbf{p}(n_0(k))), \hat{\mathbf{p}}/\delta)_k = \min\{\delta p_k(n_0(k)), \delta\mathcal{I}_k(\mathbf{p}(n_0(k))), \hat{p}_k\} \\ &= \min\{\delta\mathcal{I}_k(\mathbf{p}(n_0(k))), \hat{p}_k\} \end{aligned}$$

This can be immediately seen as otherwise there would hold $p_k(n+1) = \delta p_k(n)$ for all $n \geq 0$, and this is impossible due to power constraints. This proves the first step of the induction. Now assume that (31) is satisfied for some $n = j$. We show that this implies that (31) holds for $n = j+1$ as well. First consider the case (i): $p_k(j+1) = \hat{p}_k$. We get $p_k(j+2) = \min\{\delta\hat{p}_k, \delta\mathcal{I}_k(\mathbf{p}(j)), \hat{p}_k\} = \min\{\delta\mathcal{I}_k(\mathbf{p}(j+1)), \hat{p}_k\}$. Now, assume (ii): $p_k(j+1) = \delta\mathcal{I}_k(\mathbf{p}(j))$. In this case $p_k(j+2) = \min\{\delta^2\mathcal{I}_k(\mathbf{p}(j)), \delta\mathcal{I}_k(\mathbf{p}(j+1)), \hat{p}_k\}$. Furthermore, $\mathbf{p}(j+1) \leq \delta\mathbf{p}(j)$, so considering properties A2 and A3 yields $\delta\mathcal{I}_k(\mathbf{p}(j+1)) \leq \delta\mathcal{I}_k(\delta\mathbf{p}(j)) < \delta^2\mathcal{I}_k(\mathbf{p}(j))$. This in turn results in $p_k(j+2) = \min\{\delta\mathcal{I}_k(\mathbf{p}(j+1)), \hat{p}_k\}$ also in the case (ii), which completes the second step of the induction and the proof of the lemma. $\blacksquare$

The lemma implies that there exists n_0 such that for all $n \geq n_0$ the iteration (11) is equivalent to $\mathbf{p}(n+1) = \hat{\mathcal{I}}(\mathbf{p}(n))$ with $\hat{\mathcal{I}}(\mathbf{p}) := \min\{\delta\mathcal{I}(\mathbf{p}), \hat{\mathbf{p}}\}$. The function $\hat{\mathcal{I}}(\mathbf{p})$ is a minimum of two standard interference functions and is therefore a standard interference function itself, in the sense of Definition 1. By [3, Corollary 1], the iteration $\mathbf{p}(n+1) = \hat{\mathcal{I}}(\mathbf{p}(n))$ always converges to a unique fixed point $\bar{\mathbf{p}}$. Finally, if (C.5) holds, then there exists $\mathbf{p}^\circ$ satisfying (15), which is the unique fixed point. This completes the proof.

E. Proof of Proposition 9

Let $\mathbf{p}$ be any power vector satisfying (20). Since (C.5) holds, such a vector exists and $\mathcal{I}(\delta\mathbf{p}) < \delta\mathcal{I}(\mathbf{p}) \leq \mathbf{p} \leq \hat{\mathbf{p}}$. Thus, by continuity of $\mathcal{I}$, there is $\lambda > 1$ such that $\mathcal{I}(\lambda\delta\mathbf{p}) \leq \hat{\mathbf{p}}$ with at least one equality.

Now suppose that $\mathbf{p}(n) \leq \lambda \delta \mathbf{p}$ holds for some $n \in \mathbb{N}_0$. As $p_k(n+1) = \min\{\hat{p}_k, \delta \mathcal{I}(\mathbf{p}(n))\}$, $k \in \mathcal{A}_n$, and $p_k(n+1)/\delta \leq p_k(n) < \mathcal{I}_k(\mathbf{p}(n))$, $k \in \mathcal{B}_n$, we then have

$$\mathbf{p}(n+1) \leq \delta \mathcal{I}(\mathbf{p}(n)) \leq \delta \mathcal{I}(\lambda \delta \mathbf{p}) < \lambda \delta^2 \mathcal{I}(\mathbf{p}) \leq \lambda \delta \mathbf{p}.$$

Since this is true for any $n \in \mathbb{N}_0$, we can conclude that if (21) is satisfied for some $m \in \mathbb{N}_0$, then it holds for all $n \geq m$.

Let $n \geq m$ be arbitrary. We are going to show that $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$. By the above and A2, we have

- (i) $\mathbf{p}(n) \leq \lambda \delta \mathbf{p}$ and
- (ii) $\lambda \delta \mathbf{p} \geq \lambda \delta^2 \mathcal{I}(\mathbf{p}) \geq \delta \mathcal{I}(\lambda \delta \mathbf{p})$, $\lambda \geq 1$.

Let $k \in \mathcal{A}_n$ be arbitrary and assume that $\hat{p}_k < \delta \gamma_k I_k(\mathbf{p}(n))$, $k \in \mathcal{A}_n$. This does not impact the generality of the analysis since otherwise the ALP property is provided. Due to (i), A2 and $\mathbf{p} \leq \hat{\mathbf{p}}$, we have, for any $k \in \mathcal{A}_n$,

$$\text{SIR}_k(\mathbf{p}(n+1)) \geq \frac{\gamma_k I_k(\lambda \delta \mathbf{p})}{I_k(\min\{\delta \mathbf{p}(n), \delta \mathcal{I}(\mathbf{p}(n))\})} \geq \frac{\gamma_k I_k(\lambda \delta \mathbf{p})}{I_k(\min\{\lambda \delta^2 \mathbf{p}, \delta \mathcal{I}(\lambda \delta \mathbf{p})\})} \geq \frac{\gamma_k I_k(\lambda \delta \mathbf{p})}{I_k(\delta \mathcal{I}(\lambda \delta \mathbf{p}))}.$$

Thus, by (ii) and A3, we have $I_k(\lambda \delta \mathbf{p}) \geq I_k(\delta \mathcal{I}(\lambda \delta \mathbf{p}))$, $k \in \mathcal{A}_n$, so that $\text{SIR}_k(\mathbf{p}(n+1)) > \gamma_k$ or, equivalently, $k \in \mathcal{A}_{n+1}$. Since this is true for any $k \in \mathcal{A}_n$, we obtain $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$. By the preservation of (21), we can finally conclude that $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$ for all $n \geq m$.

F. Proof of Proposition 10

We first prove the following lemma.

Lemma 5: Suppose that (C.5) holds and $\mathbf{p} \leq \delta \mathcal{I}(\mathbf{p})$ for some $\mathbf{p} > 0$. Then, $\mathbf{p} \leq \mathbf{p}^\circ$, where $\mathbf{p}^\circ$ is defined by (15).

Proof: The proof is by contradiction. Thus, assume that $p_k > p_k^\circ$ for some $k \in \mathcal{K}$. But, as $\mathbf{p}$ and $\mathbf{p}^\circ$ are both positive vectors, this implies that there exists $\mu > 1$ such that $\mu \mathbf{p}^\circ \geq \mathbf{p}$ and $\mu p_l^\circ = p_l$ for some $l \in \mathcal{K}$. Hence, by (15), A2 and A3, we have $\mu p_l^\circ = \mu \mathcal{I}_l(\mathbf{p}^\circ) > \mathcal{I}_l(\mu \mathbf{p}^\circ) \geq \mathcal{I}_l(\mathbf{p}) \geq p_l$, which contradicts $\mu p_l^\circ = p_l$. ■

Now, since (C.5) is assumed to hold, there exists $\mathbf{p}$ with (20). By A2, we further have $\mathcal{I}(\lambda \delta \mathbf{p}) \leq \hat{\mathbf{p}}$ for some $\lambda \geq 1$ (and, in fact, $\lambda > 1$). Let $n = m \in \mathbb{N}_0$ be any time point for which (22) is fulfilled, and let $k \in \mathcal{A}_n$ be arbitrary. We can assume $\hat{p}_k < \delta \mathcal{I}_k(\mathbf{p}(n))$, so it follows from (17)

and A3 that

$$\text{SIR}_k(\mathbf{p}(n+1)) \geq \frac{\hat{p}_k}{I_k(\mathbf{p}(n+1))} \geq \gamma_k \frac{I_k(\lambda\delta\mathbf{p})}{I_k(\mathbf{p}(n+1))} \quad (32)$$

Now (22) together with Lemma 5 and [3, Lemma 1] implies that

$$\frac{\mathbf{p}(n)}{\lambda\delta} \leq \mathbf{p}^\circ \leq \mathbf{p} \quad (33)$$

where $\mathbf{p}^\circ$ is defined by (15). Proposition 9 implies that $\mathbf{p}(n+1) \leq \lambda\delta\mathbf{p}$ for any δ -valid power vector $\mathbf{p}$. Thus, by A3, we have $\mathcal{I}(\mathbf{p}(n+1)) \leq \mathcal{I}(\lambda\delta\mathbf{p})$, from which and (32) one obtains $\text{SIR}_k(\mathbf{p}(n+1)) \geq \gamma_k$. Thus, $k \in \mathcal{A}_{n+1}$ and $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$ as $k \in \mathcal{A}_n$ is arbitrary.

Finally, Proposition 9 shows that (21) (or, equivalently, (33) with $n = m$) is preserved for all $n \geq m$. Thus, $\mathcal{A}_n \subseteq \mathcal{A}_{n+1}$ for all $n \geq m$, which completes the proof.

G. Proof of Proposition 11

First consider the following simple lemma.

Lemma 6: Let $\beta \geq 1$ be arbitrary. If (24) holds for some $m \in \mathbb{N}_0$, then $\mathbf{p}(n) \leq \beta\delta\mathcal{I}(\mathbf{p}(n))$ for all $n \geq m$.

Proof: Let $n \in \mathbb{N}_0$ be any natural number for which (24) holds with $m = n$. We are going to show that (24) is satisfied for $m = n + 1$. If (24) holds with $m = n$, then, by (11) and $p_k(n) \leq \hat{p}_k$, one obtains

$$\begin{aligned} \mathbf{p}(n+1) &= \min\{\delta\mathbf{p}(n), \delta\mathcal{I}(\mathbf{p}(n)), \hat{\mathbf{p}}\} \geq \min\{\mathbf{p}(n), \delta\mathcal{I}(\mathbf{p}(n)), \hat{\mathbf{p}}\} \\ &\geq \min\{\mathbf{p}(n), \delta\mathcal{I}(\mathbf{p}(n))\} \geq \mathbf{p}(n)/\beta. \end{aligned} \quad (34)$$

On the other hand, it follows from (11) that $p_k(n+1) \leq \delta\mathcal{I}_k(\mathbf{p}(n))$ for any $k \in \mathcal{A}_n$. If $k \in \mathcal{B}_n$, then $p_k(n+1) = \delta p_k(n) \leq \delta\mathcal{I}_k(\mathbf{p}(n))$, where the last step follows from the fact that $p_k(n) \leq \mathcal{I}_k(\mathbf{p}(n))$ for each $k \in \mathcal{B}_n$. Thus, $\mathbf{p}(n+1) \leq \delta\mathcal{I}(\mathbf{p}(n))$. When combined with (34) and A2, this yields $\mathbf{p}(n+1) \leq \delta\mathcal{I}(\beta\mathbf{p}(n+1)) < \beta\delta\mathcal{I}(\mathbf{p}(n+1))$. ■

Now we use the lemma to prove the proposition. To this end, let $m \in \mathbb{N}_0$ be any time point for which (24) holds and define

$$\beta_{\max} = \min_{k \in \mathcal{K}} \frac{\delta\lambda\mathcal{I}_k(\mathbf{p}(m))/\delta\lambda}{\mathcal{I}_k(\mathbf{p}(m))}$$

where $\lambda > 1$ is defined in Proposition 10. By (24), one has $\mathbf{p}(m) \leq \beta\delta\mathcal{I}(\mathbf{p}(m)) \leq \lambda\delta^2\mathcal{I}(\mathbf{p}(m))/\delta\lambda$ for all $\beta \in [1, \beta_{\max}]$. Proposition 10 ensures the protection at time m . Moreover, by Lemma 6,

the condition (24) is preserved for all $n \geq m$ so that $A_n \subseteq \mathcal{A}_{n+1}$ for all $n \geq m$. Finally, since $1 \leq a < b$ implies

$$a\mathcal{I}(\mathbf{p}/a) = a\frac{b}{a}\frac{a}{b}\mathcal{I}(\mathbf{p}/a) \stackrel{A2}{<} b\mathcal{I}\left(\frac{a}{b}\frac{\mathbf{p}}{a}\right) = b\mathcal{I}(\mathbf{p}/b)$$

for any fixed $\mathbf{p}$, the function $\mathbb{R}_{++} \rightarrow \mathbb{R}_{++} : x \mapsto x\mathcal{I}(\mathbf{p}(m)/x)$ is strictly increasing and, by Proposition 1, continuous in every component. Thus, we have $\beta_{\max} > 1$ as $\delta\lambda > 1$, which completes the proof.

REFERENCES

- [1] N. Bambos, S.C. Chen, and G.J. Pottie, “Channel access algorithms with active link protection for wireless communication networks with power control,” *IEEE/ACM Trans. Networking*, vol. 8, no. 5, pp. 583–597, October 2000.
- [2] G.J. Foschini and Z. Miljanic, “A simple distributed autonomous power control algorithm and its convergence,” *IEEE Trans. Veh. Technol.*, vol. 42, no. 4, pp. 641–646, Nov. 1993.
- [3] R.D. Yates, “A framework for uplink power control in cellular radio systems,” *IEEE J. Select. Areas Commun.*, vol. 13, no. 7, pp. 1341–1347, September 1995.
- [4] M. Schubert and H. Boche, “Qos-based resource allocation and transceiver optimization,” *Foundation and Trends in Communications and Information Theory*, vol. 2, no. 6, 2006.
- [5] S. Ulukus and A. Yener, “Iterative transmitter and receiver optimization for CDMA networks,” *IEEE Trans. Wireless Commun.*, vol. 3, no. 6, pp. 1879–1884, Nov. 2004.
- [6] J. M. Aein, “Power balancing in systems employing frequency reuse,” *COMSAT Tech. Rev.*, vol. 3, no. 2, pp. 277–300, 1973.
- [7] J. Zander, “Distributed cochannel interference control in cellular radio systems,” *IEEE Trans. Veh. Technol.*, vol. 41, pp. 305–311, August 1992.
- [8] R.D. Yates and C.Y. Huang, “Integrated power control and base station assignment,” *IEEE Trans. Veh. Technol.*, vol. 44, no. 3, pp. 638–644, August 1995.
- [9] D. Gerlach and A. Paulraj, “Base station transmitting antenna arrays for multipath environments,” *Signal Processing (Elsevier Science)*, vol. 54, pp. 59–73, 1996.
- [10] N. Bambos, “Toward power-sensitive network architectures in wireless communications: Concepts, issues, and design aspects,” *IEEE Personal Commun. Mag.*, vol. 5, pp. 50–59, June 1998.
- [11] Qiang Wu, “Optimum transmitter power control in cellular systems with heterogeneous SIR thresholds,” *IEEE Trans. Veh. Technol.*, vol. 49, no. 4, pp. 1424–1429, July 2000.
- [12] J. Zander and S.-L. Kim, *Radio Resource Management for Wireless Networks*, Artech House, Boston, London, 2001.
- [13] T. ElBatt and A. Ephremides, “Joint scheduling and power control for wireless ad hoc networks,” *IEEE Trans. Wireless Commun.*, vol. 3, no. 1, pp. 74–85, January 2004.
- [14] M. Chiang, P. Hande, T. Lan, and C.W. Tan, “Power control in wireless cellular networks,” *Found. Trends Netw.*, vol. 2, no. 4, pp. 381–533, 2008.
- [15] S.V. Hanly, “An algorithm for combined cell-site selection and power control to maximize cellular spread spectrum capacity,” *IEEE Journal on Selected Areas in Communications*, vol. 13, no. 7, pp. 1332–1340, 1995.

- [16] H. Boche and M. Schubert, "Concave and convex interference functions: general characterizations and applications," *Signal Processing, IEEE Transactions on*, vol. 56, no. 10, pp. 4951–4965, Oct. 2008.
- [17] H. Boche and M. Schubert, "A calculus for log-convex interference functions," *Information Theory, IEEE Transactions on*, vol. 54, no. 12, pp. 5469–5490, Dec. 2008.
- [18] M. Fazel, D. M. Gayme, and M. Chiang, "Transient analysis for wireless power control," in *Global Telecommunications Conference, 2006. GLOBECOM '06. IEEE*, 2006.
- [19] F. Cuomo and C. Martello, "Improving wireless access control schemes via adaptive power regulation," in *In Proceedings of PWC 2003*, 2003, pp. 114–127.
- [20] T. Alpcan, X. Fan, T. Basar, M. Arcak, and J. T. Wen, "Power control for multicell cdma wireless networks: a team optimization approach," *Wireless Networks*, vol. 14, no. 5, pp. 647–657, 2008.
- [21] S.H.R. Naqvi and L.M. Patnaik, "A distributed channel access protocol for ad hoc networks with feedback power control," *IEEE Trans. Mobile Comput.*, vol. 5, no. 10, pp. 1448–1459, Oct. 2006.
- [22] F. Baccelli, B. Błaszczyszyn, and M. K. Karray, "Up- and downlink admission/congestion control and maximal load in large homogeneous cdma networks," *Mob. Netw. Appl.*, vol. 9, no. 6, pp. 605–617, 2004.
- [23] J. T. Wang, "Admission control with distributed joint diversity and power control for wireless networks," *IEEE Trans. Veh. Technol.*, vol. 58, no. 1, pp. 409–419, Jan. 2009.
- [24] Z. Marantz, P. Orenstein, and D.J. Goodman, "Admission control for maximal throughput in power limited cdma systems," in *Wireless Communications and Networking Conference (WCNC)*, March 2005, vol. 2, pp. 695–700.
- [25] D. Liu, Y. Zhang, and S. Hu, "Call admission policies based on calculated power control setpoints in SIR-based power-controlled ds-cdma cellular networks," *Wireless Networks*, vol. 10, pp. 473–483, 2004.
- [26] C. M. Chin, M. L. Sim, and S. Olafsson, "Call admission control with adaptive active link protection for wireless systems," in *Proc. IEEE Vehicular Techn. Conf. (VTC)*, May 2006, vol. 5, pp. 2454–2458.
- [27] L. Jurgens, A. Dekorsy, and J. Fliege, "A homotopy method for call admission control employing different user and service classes," in *16th IEEE Symposium on Personal, Indoor and Mobile Radio Communications, (PIMRC)*, Berlin, Germany, Sept. 11–14 2005, vol. 3, pp. 1880–1884.
- [28] R. Mathar and A. Schmeink, "Proportional QoS adjustment for achieving feasible power allocation in CDMA systems," *IEEE Trans. Commun.*, vol. 56, no. 2, pp. 254–259, Feb. 2008.
- [29] J. Huang, R. Berry, A. Berry, and M. L. Honig, "Auction-based spectrum sharing," in *University of Cambridge*, 2004, pp. 405–418.
- [30] J. Huang, R. Berry, and M. L. Honig, "Distributed interference compensation for wireless networks," *IEEE J. Select. Areas Commun.*, vol. 24, no. 5, pp. 1074–1084, May 2006.
- [31] M. Xiao, N. B. Shroff, and E. K. P. Chong, "Distributed admission control for power-controlled cellular wireless systems," *IEEE/ACM Trans. Networking*, vol. 9, no. 6, pp. 790–800, 2001.
- [32] A. Koskie and Z. Gajic, "A Nash game algorithm for SIR-based power control for 3G wireless CDMA networks," *IEEE/ACM Trans. Networking*, vol. 13, no. 5, pp. 1017–1026, Oct. 2005.
- [33] M. Xiao, N.B. Shroff, and E.K.P. Chong, "A utility-based power control scheme in wireless cellular systems," *IEEE/ACM Trans. Networking*, vol. 11, no. 2, pp. 210–221, April 2003.
- [34] C. W. Tan, D. P. Palomar, and M. Chiang, "Exploiting hidden convexity for flexible and robust resource allocation in cellular networks," in *Proc. 26th IEEE International Conference on Computer Communications (INFOCOM)*, May 2007, pp. 964–972.

- [35] J. Mitola III, *An Integrated Agent Architecture for Software Defined Radio*, Ph.D. thesis, Computer Communication System Laboratory, Department of Teleinformatics, Royal Institute of Technology (KTH), Stockholm, Sweden, 2000.
- [36] I. F. Akyildiz, W.-Y. Lee, M. C. Vuran, and S. Mohanty, "Next generation/dynamic spectrum access/cognitive radio wireless networks: a survey," *Comput. Netw.*, vol. 50, no. 13, pp. 2127–2159, 2006.
- [37] I. Mitliagkas, N.D. Sidiropoulos, and A. Swami, "Convex approximation-based joint power and admission control for cognitive underlay networks," in *International Wireless Communications and Mobile Computing Conference (IWCMC)*, Aug. 2008, pp. 28–32.
- [38] E. A. Jorswieck and H. Boche, "Performance analysis of capacity of MIMO systems under multiuser interference based on worst case noise behavior," *EURASIP Journal on Wireless Communications and Networking*, vol. 2, pp. 273–285, 2004.
- [39] H. Boche and M. Schubert, "A unified framework for interference modeling for multi-user wireless networks," in *Proc. IEEE International Conference on Communications (ICC)*, Dresden, Germany, June 2009.
- [40] S. Stanczak, M. Wiczanowski, and H. Boche, *Fundamentals of Resource Allocation in Wireless Networks*, vol. 3 of *Foundations in Signal Processing, Communications and Networking*, Springer, Berlin, 2009.
- [41] S. Verdu, *Multiuser Detection*, Cambridge University Press, 1998.
- [42] S. Stanczak, M. Kaliszan, and N. Bambos, "Admission control for power-controlled wireless networks under general interference functions," in *Proc. 42nd Asilomar Conference on Signals, Systems, and Computers*, Monterey, CA, USA, Oct. 2008.